




# RMF – Role Synchronization

Vega Systems Inc.

03/15/2023

<https://www.vega25.com/rmf>



**Step 1:** Open the **Management Client**.

**Note:** Run as administrator

Milestone  
XProtect® Management Client 2022 R3

Computer:  
primaryrec1.vegadomn.com

Authentication:  
Windows authentication

Domain: vegadomn.com

User name:  
vegadomn.com\milestone

Password:  
••••••••

Remember password

Sign in Close

Management Server

**Step 2:** Login into the **Parent Management Server** as a domain user with admin privileges. (Federated Deployments)  
**Login into Management Server** as a user with admin privileges (Non-Federated Deployments)



Milestone XProtect Management Client 2022 R3

File View Action Maintenance Tools Help

Site Navigation Configuration

Axis One-click Camera Connection

- Servers
  - Recording Servers
  - Failover Servers
  - Mobile Servers
- Devices
  - Cameras
  - Microphones
  - Speakers
  - Metadata
  - Input
  - Output
- Client
  - Smart Wall
  - View Groups
  - Smart Client Profiles
  - Management Client Profiles
  - Matrix
- Rules and Events
  - Rules
  - Time Profiles
  - Notification Profiles
  - User-defined Events
  - Analytics Events
  - Generic Events
- Security
  - Roles
  - Basic Users
- System Dashboard
  - Current Tasks
  - System Monitor
  - System Monitor Thresholds
  - Evidence Lock
  - Configuration Reports
- Server Logs
- Metadata Use
  - Metadata Search
- Access Control
- Incidents
  - Incident properties
- Transact
  - Transaction sources
  - Transaction definitions
- Alarms
  - MIP Plug-ins
  - RMF
    - Redundancy Configuration
    - Alarms
    - Service Configuration


Configuration

Please Select An Option

- Start From Clean Slate
- Recording Server Synchronization
- Manage RMF Licenses
- Modify Connection Priority
- Role Synchronization**
- Modify Playback
- Modify Switch Time
- Modify Overlay Settings
- Modify WebAPI Port
- Modify RMF Logging
- Refresh RMF Alarms
- Export Logs

Site Navigation Federated Site Hierarchy


**Step 4:** Goto Redundancy Configuration.  
Select **Role Synchronization** from the list.



**Step 5:** The **RMF Role Replicator** helps to synchronize roles and camera access rights seamlessly from the parent (**primary**) site to the child (**secondary**) site.



Refer to **Setting up High Availability Roles & Smart Client Views** for adding roles to the parent (primary) site and role replication.



**Step 6: Click Launch Role Replicator.**



Roles

### Connect to Site

Management Server address and credentials

Server:


Authentication:

Username:

Password:

**Note:** If you're in an XProtect Federated Setup, please log in to the parent management server.

**Step 7: Login** into the **Parent Management Server** as a domain user with admin privileges. (Federated Deployments)  
**Login** into the **Management Server** as a user with admin privileges. (Non-Federated Deployments)



**Step 8:** The process may take several minutes based on the number of cameras and roles.  
Click **Next**.



Roles - Add/Sync


RMF Cameras	Progress	Status	Result
AXIS M3044-V Network Camera (172.16.0.3) - Camera 1	<div style="width: 100%;"></div>	Re-check	
AXIS M3044-V Network Camera (172.16.0.3) - Camera 2	<div style="width: 100%;"></div>	Re-check	
AXIS M5013 PTZ Dome Network Camera (172.16.0.4) - Camera 1	<div style="width: 100%;"></div>	Re-check	
ONVIF IP4DIR100 (172.16.0.12) - Camera 1	<div style="width: 100%;"></div>	Re-check	

Please wait while RMF synchronizes camera role settings across recording servers.

sales@vega25.com

**Step 10:** Re-checking or Syncing roles in progress.





**Step 12: Click Finish.**